



JVA Fault Finder

PTE0129

Overview:

If the JVA Fault Finder looks familiar it is because it is made by Pakton, the company who invented the direction fault finder in 1991. This latest generation Fault Finder is rugged and reliable and proudly Australian Made.

Features:

- Water proof design
- Integrated (removable) belt clip
- Longer lasting battery
- Ergonomic case design
- Fingers are further away from High Voltage
- Bright red LED direction arrows
- 1 touch operation – Simple to use
- Clear indications of the direction of the fault
- Digital readout which shows fence voltage and current
- No wires, No clips, No tangles, No Shocks!
- Pocket size – Easy to carry
- Displays direction to a “high load” fault, not just current flow
- Will take you right to the fault, not leave you metres short!

Specifications:

Voltage	Display: Range: Accuracy:	2 Digit 10mm LCD 0 – 9.9kV ^[1] +/- 10%
Current	Display: Range: Accuracy:	2 Digit 10mm LCD 0-30Amp ^[2] +/-10%
Size	Height: Width: Depth:	155 mm 60 mm 24 mm
Weight	Product: Packed:	0.1530kg 0.1960kg

[1] Not recommended for use at higher than 9.9kV

[2] Higher currents read as 30Amp

Package Contents:

- JVA Fault Finder (PTE0129), battery included.
- Instruction Manual



Warranty:

3 Year Manufacturer Warranty

